

BEYOND CCTV & BIO

BizEzi DS100

Dual Fingerprint Sensor
Time & Attendance Terminal



Features:

- Dual Fingerprint Sensors, Twice the speed
- Reliable, durable and highly accurate ZK optical sensors with version 10 fingerprint algorithm
- Less than 1 second user recognition
- Built-in 125kHz RFID proximity reader
- Colour TFT screen with GUI
- Reads finger and/or RFID cards
- Built-in TCP/IP port
- Built-in USB port for manual data transfer
- Audio – Visual indication for acceptance and rejection of valid/ invalid fingers
- Built-in battery backup

Specifications:

Fingerprint Capacity:	3000 templates
Transaction Capacity:	100 000 transactions
Sensor:	USA Optical Sensor
Algorithm Version:	Finger V10.0
Display:	3 inch Colour TFT Screen
Communications:	TCP/IP, USB - Host, SD Card
Built-in Card Reader:	125kHz RFID proximity reader
Power Supply:	12VDC, 3A
Dimensions:	251x134x54 mm
Battery Backup:	Built-in

Beyond CCTV & BIO Tel: 011 029 3711/2/3

E-mail: info@beyondcctvandbio.co.za

Website: www.beyondcctvandbio.co.za

An authorised dealer of 